

Parts Export

Generated: 2026-06-10 08:23:21

Total Parts: 1

Image	Part Number	Name	Category	Manufacturer	Description	Specification	Tags
No Image	EMS-00001-A	MQ-2 sensor	EM - Electronic-Electrical Modules	Hanwei Electronics Group Corporation, Zhengzhou Winsen Electronics Technology Co., Ltd.	The MQ-2 Gas Sensor Module detects combustible gases such as LPG, methane, hydrogen, alcohol vapor, and smoke. It uses a SnO ₂ sensing element and provides both analog and digital outputs with adjustable sensitivity. Ideal for gas leakage detection, safety systems, and Arduino-based environmental monitoring projects.	Sensor Model: MQ-2 Detection Range: 300 – 10,000 ppm Detectable Gases: LPG, Butane, Propane, Methane (CH ₄), Hydrogen (H ₂), Alcohol, Smoke, CO Sensing Material: Tin Dioxide (SnO ₂) Operating Voltage: 5V DC Digital Output Voltage: 0V or 5V (TTL Logic) Analog Output: Yes Sensitivity Adjustment: Onboard Potentiometer Preheat Time: 20 seconds (minimum) Dimensions (mm): 36 x 20 x 21 Weight (g): 8 Shipping Weight: 0.012 kg Shipping Dimensions (cm): 4 x 4 x 4	Arduino Compatible • MQ-2 Sensor • LPG Gas Sensor • Smoke Detector • SnO ₂ Sensor • Combustible Gas Module • 5V Gas Sensor • Gas Leakage Detector