

Parts Export

Generated: 2026-06-10 07:37:23

Total Parts: 2

Image	Part Number	Name	Category	Manufacturer	Description	Specification	Tags
No Image	EDD-00004-A	1 Digit 7-Segment LED Display	ED - Electronic Device	Lite-On Technology, Kingbright, Generic / OEM	The 0.56" 1-Digit 7-Segment LED Display is designed to display decimal numbers (0-9) using seven LED segments. It features a common cathode configuration with bright red LEDs for clear and efficient numeric indication. Ideal for digital clocks, counters, meters, and microcontroller-based display applications.	Model: 7 Segment LED Display Digit Count: 1 Digit Display Size: 0.56 Inch Configuration Type: Common Cathode Emitting Color: Red Face Color: Black Number of Pins: 10 Forward Voltage (V): 1.8 – 2.2 (Typical for Red LED) Forward Current (mA): 20 (Typical) Mounting Type: PCB Through Hole Characteristics: High Brightness, Low Current Consumption, Easy to Use Length (Inch): 0.56 Shipping Weight: 0.02 kg Shipping Dimensions (L x W x H cm): 6 x 4 x 2	Arduino Compatible • 0.56" 7-Segment • 1 Digit Display • Red LED • Common Cathode • 5161AS • Through Hole • Numeric Display
No Image	EDD-00004-B	7 Segment Display, 1 digit device	ED - Electronic Device	Kingbright, Lite-On, Everlight, Broadcom	Single digit common anode 7 segment LED display device designed for numeric indication in embedded systems, counters, timers, clocks, measurement instruments, and electronics projects. It provides bright numeric visualization with low power consumption and simple interfacing using microcontrollers and digital logic circuits. Commonly used in Arduino projects, digital counters, calculators, industrial control panels, and educational electronics applications.	Display Type: 1 Digit 7 Segment LED Display Configuration: Common Anode Operating Voltage: 1.8V – 2.2V per Segment Number of Pins: 10 Pins Digit Height: 0.36 Inch – 0.56 Inch	Numeric Display • 7 segment display • common anode display • single digit display • LED display